

User Guide - FLCTD1S

RF Control - Single Zone Desk Rotary Dimmer



Features

- Use with our single colour LED receiver FLDC1S
- Sensitive color adjustment touch wheel.
- 2.4GHz wireless technology, control distance up to 30m.
- Pair with one or multiple receivers.
- Battery powered (CR2032).
- LED light indicator on the remote.

Technical Paramteres

- Output signal: RF(2.4GHz)
- Input Voltage: Battery (CR2032)
- Light Type: Single Colour
- Dimesions: 86x86x35 mm
- Remote distance up to 30m within Free Range. Please allow for 12m within areas restricted by obstacles.

Pairing Guide

Pair the controller with our 2.4G RF receiver (FLDC1S). There are two pairing methods:

- Using the "Match Key"

Match the controller with our receiver (Using the Match Key on the receiver)

1. Match: Short press the match key, then Push the wheel wheel within 3s.
2. To Delete a Match: Long press the match key on the receiver for 5s.

- At Power Up

Match the controller with our receiver (Without using the Match Key)

1. Match: Switch off receiver power, then switch on power again, short press the remote wheel 3 times within 3 seconds. The link has been completed once the connected LED lights flash 3 times.
2. To Delete a match: Switch off power to the receiver, then switch on power again, short press controller wheel 5 times on the remote within 3s after power on, the unlink has been completed once the connected LED lights flash 5 times.

Key Functions



Dimensions

